Intelligent Controllers / Collaborators

CLTP SERIES





INTELLIGENT CONTROLLERS / COLLABORATORS - CTLP SERIES

The core of the TraffiCalm® Flashing Sign systems, the Intelligent Controllers and Collaborators, are the "brains" of the group. These devices handle everything from flash rate to automatic brightness control to scheduling.

......

Each Controller or Collaborator allows inputs from a TraffiCalm Smart Radar Sensor and one additional activation device, like a pushbutton or a sensor. Additionally, it has outputs for two flashing LED rings, rectangular rapid flashing beacons, or round beacons, for example. The possibilities of Flashing Sign Systems are endless.

FEATURES

Easy Configuration and Setup

Quick configuration via TC-Connect, a Wi-Fi connection platform developed by TraffiCalm that requires NO internet connection! With any browser-enabled device, the installer can easily log on and select from multiple options and settings, including flash duration, LED brightness, and dimming control. Optional TC-Remote compatible controllers allow agencies to remotely connect to multiple TraffiCalm Flashing Sign Systems in one easy-to-manage web-based platform.

Ruggedized Electronics

All electronics are fully epoxy-potted and environmentally sealed. The entire Controller or Collaborator, radar, and Flashing LED Sign Ring can be fully submerged and still operate.

One Controller - Multiple Applications

Each TraffiCalm Intelligent Controller or Collaborator can be configured to be an All-Flash System, Push-2-Cross System, Sequencing Chevron System, Conflict Intersection or High Water Warning System.

Made in the USA

TraffiCalm Controllers and Collaborators are manufactured in the USA in an ISO 9001:2015-certified facility. In addition, we provide unlimited technical phone support for the life of the unit. Build America/Buy America Compliant.

TRAFFICALM.COM

CTLP Series THAFFICALM®

SPECIFICATIONS

PHYSICAL DESCRIPTIONS

Mounting: Universal bracket accommodates most industry standard round or square posts of suitable load rating

Designed for retrofit installation to existing infrastructure

Aluminum cabinet with brass lock with type II key

All electronics potted for weatherproofness

Stainless fasteners used for corrosion resistance

-40° F to +140° F (-40°C to 60° C) operating range

INPUT/OUTPUT

Inputs: 2 per Controller. Optional input devices include push buttons, environmental sensors, over-height sensors, and others

Outputs: 2 per Controller or Collaborator, 12W max requirement. Output devices include: Sign Rings, Rectangular Rapid Flashing Beacons (RRFBs), and Round Beacons

Radar Port: Accepts input from TraffiCalm® Smart Radar Sensor

Light sensor for configurable auto-dimming feature based on ambient light conditions

SYSTEM REQUIREMENTS

Each "system" will have a maximum of one Controller. Additional signs on separate poles or posts in the system are run by Collaborators. For example, in a crosswalk, there should be one Controller on one side of the street and one Collaborator on the other side of the street. When a push button is activated on either side of the street, both poles with rectangular rapid-flashing beacons and rings flash simultaneously.

Controller/Collaborator with Side-of-Pole Mounted Enclosures

Power	AC Power
Intelligent Controller	M75-SA300-CTLP
Weight	22 lbs/10 kg
Outside Dimensions	6"w x 11.63"h x 15.75"d (15.24 cm, 29.54 cm, 40 cm)
AC/Solar	Integrated AC
Battery	Does not apply
Solar Panel	Does not apply
AC Input	0.43A/100-277VAC
Cabinets	Aluminum Cabinet with padlock latch

TC-CONNECT™ USER INTERFACE

Wi-Fi Connectivity: No Internet Connection required

Mode Selection: Pedestrian Crossing, Curve Warning, All Flash, Conflict Intersection, High Water Warning

Configurable Flash Duration (60 flashes/minute by default)

Retrievable activation logs are stored for at least 365 days

On screen status reporting includes: Controller to Collaborator(s) signal strength, Controller and Collaborator(s) flasher output voltages, Controller and Collaborator(s) input voltage (battery or AC devices), Controller and Collaborator(s) charging voltage, Controller and Collaborator(s) firmware version

RADIO COMMUNICATION BETWEEN CONTROLLERS and COLLABORATORS

Wireless activation within 100 milliseconds

Wireless range of 3,500 ft/1066.8 m line of sight, 1,500 ft/457 m non-line of sight.

2.4 GHz radios

WARRANTY and SERVICE

5-year limited warranty, 1-year on batteries

Unlimited tech support from US based factory technicians



